

# Differential Impedance TDR Probes for the DSA8300\*1

## P80318 • P80318X Data Sheet



### Features & Benefits

- 18 GHz Bandwidth
- Direct In-circuit TDR Testing
- Reliable and Repeatable Resolution of Impedance Variations to 0.12 in.
- Adjustable Probe Pitch from 0.5 mm to 4.2 mm
- Probing of Fully Balanced Differential Signals without Ground Contact
- Double-cushioning Design enables Probe Tips to Maintain Proper DUT Contact
- Protects Sampling Module from Static Damage when used with Two 80A02 Modules

### Applications

- Circuit-board Controlled Impedance Testing (TDR)
- Loss Tangent Measurements for Differential Transmission Lines
- Failure Analysis of PCB with or without Components Mounted
- Package Impedance Testing (TDR)

### P80318

The P80318 is an 18 GHz 100  $\Omega$  input impedance differential TDR hand probe. This probe enables high-fidelity impedance measurements of differential transmission lines. The adjustable probe pitch enables a wide variety of differential line spacing and impedances. The P80318 probe also includes two precision SMA cables with parallel control lines that provide the 80A02 the control for EOS/ESD protection.

### P80318X

The P80318X is designed for high-volume PCB impedance test applications. These applications require maximum manufacturing up-time. The P80318X includes everything in a P80318 plus a second probe body for use if the first probe body needs to be serviced due to normal wear.

The P80318 probe can be used as a stand-alone high-resolution probe, but it is specially designed to be used with two 80A02 EOS/ESD Protection modules. To maximize testing up-time and minimize repair costs, protecting the sampling module from static damage is a requirement. Damage to the sampling module is typically due to electro-overstress (EOS) and electrostatic discharge (ESD) from large static charges stored in the DUT. Use of two 80A02 modules ensures proper probe grounding prior to switching signal to the sampling module.

\*1 Also compatible with DSA8200, TDS/CSA8200, TDS/CSA8000B, TDS/CSA8000 sampling oscilloscopes.

- ASEAN / Australasia (65) 6356 3900
- Austria 00800 2255 4835\*
- Balkans, Israel, South Africa and other ISE Countries +41 52 675 3777
- Belgium 00800 2255 4835\*
- Brazil +55 (11) 3759 7627
- Canada 1 800 833 9200
- Central East Europe and the Baltics +41 52 675 3777
- Central Europe & Greece +41 52 675 3777
- Denmark +45 80 88 1401
- Finland +41 52 675 3777
- France 00800 2255 4835\*
- Germany 00800 2255 4835\*
- Hong Kong 400 820 5835
- India 000 800 650 1835
- Italy 00800 2255 4835\*
- Japan 81 (3) 6714 3010
- Luxembourg +41 52 675 3777
- Mexico, Central/South America & Caribbean 52 (55) 56 04 50 90
- Middle East, Asia, and North Africa +41 52 675 3777
- The Netherlands 00800 2255 4835\*
- Norway 800 16098
- People's Republic of China 400 820 5835
- Poland +41 52 675 3777
- Portugal 80 08 12370
- Republic of Korea 001 800 8255 2835
- Russia & CIS +7 (495) 7484900
- South Africa +41 52 675 3777
- Spain 00800 2255 4835\*
- Sweden 00800 2255 4835\*
- Switzerland 00800 2255 4835\*
- Taiwan 886 (2) 2722 9622
- United Kingdom & Ireland 00800 2255 4835\*
- USA 1 800 833 9200

\* European toll-free number. If not accessible, call: +41 52 675 3777

Updated 10 February 2011

## Characteristics

Characteristic	Description
Nominal Length with Cable	1 m
Attenuation	1X
Probe-only Bandwidth	>20 GHz
Probe Pitch	0.5 to 4.2 mm (signal tip to signal tip)
Connector Type	SMA
Measured Reflected TDR Fall Time	<39 ps
Impedance	50 $\Omega$ odd mode, 100 $\Omega$ differential
Max $V_{IN}$	5.0 V
Probe-only Propagation Delay	1.0 ns typical
TDR Control Activation Force	150 to 200 g, each probe half

Note: Numeric values shown are typical.

## Ordering Information

### P80318

18 GHz 100  $\Omega$  Differential TDR Hand Probe.

**Includes:** 18 GHz bandwidth, 50  $\Omega$  odd mode input impedance (100  $\Omega$  differential impedance), differential passive handheld probe with one set of two precision SMA cables, soft storage case, user manual, and three replaceable ground shorting straps.

### P80318X

18 GHz 100  $\Omega$  Differential TDR Hand Probe for Manufacturing.

**Includes:** Two 18 GHz bandwidth, 50  $\Omega$  odd mode input impedance (100  $\Omega$  differential impedance), differential passive handheld probes with one set of two precision SMA cables, soft storage case, user manual, and three replaceable ground shorting straps. Second probe body is provided as a backup to the first to maximize manufacturing up-time if the first probe body needs to be serviced due to wear.

## Recommended Accessories

Characteristic	Description
P8018	18 GHz Single-ended 50 $\Omega$ TDR Probe. To compliment TDR probing for single-ended applications
80A02	ESD/EOS TDR Protection Module
174-3896-xx	External Probe Power Cable. To reduce module acquisition slot consumption the 80A02 modules can run off this probe power cable
020-2670-xx	Ground Spring Kit. Set of two ground springs with a spare set screw for P80318 probe

**For Further Information.** Tektronix maintains a comprehensive, constantly expanding collection of application notes, technical briefs and other resources to help engineers working on the cutting edge of technology. Please visit [www.tektronix.com](http://www.tektronix.com)



Copyright © Tektronix, Inc. All rights reserved. Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX and TEK are registered trademarks of Tektronix, Inc. All other trade names referenced are the service marks, trademarks, or registered trademarks of their respective companies.

28 Apr 2011

85W-18863-2

