

# Isolated Measurement Systems

## TIVM1, TIVM1L, TIVH08, TIVH08L, TIVH05, TIVH05L, TIVH02, TIVH02L Datasheet



Tektronix TIVM 및 TIVH 시리즈 IsoVu™ 측정 시스템은 넓은 공통 모드 전압이 있을 때 최대 ± 2500V의 고 대역폭 차동 신호를 정확하게 해결하기 위해 갈바닉 절연 측정 솔루션을 제공합니다.

### 특징 및 장점

- Bandwidths from DC to 1 GHz
- 100 Million to 1 (160 dB) Common Mode Rejection from DC up to 1 MHz
- 10,000 to 1 (80 dB) Common Mode Rejection at 1 GHz
- 60 kV peak Common Mode Voltage
- Up to ±2500 V Differential (DC + pk AC)
- Up to ±2500 V offset range
- Output clamping
- Safety certified
- DC and AC input coupling

### 적용 분야

- Half/Full Bridge designs using GaN, SiC, IGBTs
- Floating measurements
- Power Converter design
- Power Device evaluation
- Switching Power Supply design
- Inverter design
- Motor Drive design
- Electronic Ballast design
- EMI
- ESD
- Current shunt measurements
- Remote probing capability

### 제품 설명

TIVM 및 TIVH 시리즈 (IsoVu) 제품은 TekVPI 인터페이스가 있는 대부분의 Tektronix 오실로스코프와 TCA-VPI50 어댑터가 있는 MSO / DPO70K 시리즈 오실로스코프에서 사용할 수 있습니다. IsoVu는 센서 팁 케이블의 전기 신호를 광학 신호로 변환하는 전기 광학 센서를 사용하여 테스트 대상 장치를 오실로스코프에서 전기적으로 분리합니다. IsoVu는 4개의 개별 레이저, 광학 센서, 5개의 광섬유 및 정교한 피드백 및 제어 기술을 통합합니다. 테스트 지점에 연결되는 센서 헤드는 전기적으로 완전히 절연되어 있으며 광섬유 중 하나를 통해 전원이 공급됩니다 (배터리 불필요). IsoVu는 다음과 같은 측정을 수행하는 사용자에게 이상적인 솔루션입니다.

- 다음 조건에서의 차동 측정
  - 완전한 갈바닉 절연이 필요합니다.
  - 높은 공통 모드 전압
  - 고주파 공통 모드 간섭
  - 고주파수 측정
- 높은 EMI 환경에서의 측정
- EMI 적합성 테스트
- ESD 테스트

## 제품 사양

별도로 명시되지 않는 한 모든 사양이 보장됩니다. 별도로 명시되지 않는 한 모든 사양은 모든 모델에 적용됩니다.

### 개요

Characteristic	TIVM1/TIVM1L	TIVH08/TIVH08L	TIVH05/TIVH05L	TIVH02/TIVH02L
Bandwidth/Rise time (Typical)	1 GHz / $\leq 350$ ps	800 MHz / $\leq 435$ ps <sup>1</sup>	500 MHz / $\leq 700$ ps	200 MHz / $\leq 1.8$ ns
Fiber cable length	TIVM1: 3 m (9.8 ft) TIVM1L: 10 m (32.8 ft)	TIVH08: 3 m (9.8 ft) TIVH08L: 10 m (32.8 ft)	TIVH05: 3 m (9.8 ft) TIVH05L: 10 m (32.8 ft)	TIVH02: 3 m (9.8 ft) TIVH02L: 10 m (32.8 ft)

### TIVM 시리즈 감쇠, 차동 입력 전압 범위, 오프셋 범위, 차동 임피던스 (일반)

아래에 나열된 센서 팁 케이블 만 TIVH 시리즈와 함께 사용하십시오.

Sensor tip cable	Attenuation	Differential input voltage		Offset range	Input impedance
		1X range	2X range		
SMA input	1X	$\pm 0.5$ V	$\pm 1$ V	$\pm 2$ V	50 $\Omega$    N.A.
<b>MMCX sensor tip cables</b>					
IVTIP1X	1X	$\pm 0.5$ V	$\pm 1$ V	$\pm 2$ V	50 $\Omega$    N.A.
IVTIP5X	5X	$\pm 2.5$ V	$\pm 5$ V	$\pm 10$ V	250 $\Omega$    $<1$ pF
IVTIP10X	10X	$\pm 5$ V	$\pm 10$ V	$\pm 20$ V	500 $\Omega$    $<1$ pF
IVTIP25X	25X	$\pm 12.5$ V	$\pm 25$ V	$\pm 50$ V	1.25 k $\Omega$    $<1$ pF
IVTIP50X	50X	$\pm 25$ V	$\pm 50$ V	$\pm 100$ V	2.5 k $\Omega$    $<1$ pF

### TIVH 시리즈 감쇠, 차동 입력 전압 범위, 오프셋 범위, 차동 임피던스 (표준)

아래에 나열된 센서 팁 케이블 만 TIVH 시리즈와 함께 사용하십시오.

Sensor tip cable	Attenuation	Differential input voltage		Offset range	Input impedance
		1X range	2X range		
SMA input	1X	$\pm 0.5$ V	$\pm 1$ V	$\pm 25$ V	1 M $\Omega$    20 pF
<b>MMCX sensor tip cables</b>					
IVTIP1X	1X	$\pm 0.5$ V	$\pm 1$ V	$\pm 25$ V	1 M $\Omega$    35 pF <sup>2</sup>
MMCX10X	10X	$\pm 5$ V	$\pm 10$ V	$\pm 250$ V	10 M $\Omega$    6 pF
MMCX50X	50X	$\pm 25$ V	$\pm 50$ V	$\pm 250$ V	10 M $\Omega$    3 pF
MMCX250X	250X	$\pm 125$ V	$\pm 250$ V	$\pm 250$ V	10 M $\Omega$    2 pF
<b>0.100 in Pitch (2.54 mm) Square Pin sensor tip cables</b>					
SQPIN100X	100X	$\pm 50$ V	$\pm 100$ V	$\pm 600$ V	10 M $\Omega$    3.5 pF
SQPIN500X	500X	$\pm 250$ V	$\pm 500$ V	$\pm 600$ V	10 M $\Omega$    3.5 pF
<b>0.200 in Pitch (5.08 mm) Square Pin sensor tip cables</b>					
WSQPIN1000X	1000X	$\pm 500$ V	$\pm 1000$ V	$\pm 2500$ V	40 M $\Omega$    3.5 pF
WSQPIN2500X	2500X	$\pm 1250$ V	$\pm 2500$ V	$\pm 2500$ V	40 M $\Omega$    3.5 pF

<sup>1</sup> The 800 MHz bandwidth is achieved with the 50X and greater attenuation tips (MMCX50X, MMCX250X, SQPIN100X, SQPIN500X, WSQPIN1000X, or WSQPIN2500X).

<sup>2</sup> With 6-inch tip cable sensor head 20 pF plus cable 15 pF.

## TIVM 시리즈 공통 모드 제거율, 센서 팁 케이블 및 어댑터 (일반)

Sensor tip cable/adaptor	DC	1 MHz	100 MHz	200 MHz	500 MHz	1 GHz
<b>MMCX Sensor tip cables</b>						
IVTIP1X	160 dB	124 dB	120 dB	110 dB	100 dB	90 dB
IVTIP5X	160 dB	124 dB	120 dB	110 dB	100 dB	90 dB
IVTIP10X	160 dB	124 dB	120 dB	110 dB	100 dB	90 dB
IVTIP25X	160 dB	120 dB	110 dB	100 dB	100 dB	90 dB
IVTIP50X	160 dB	116 dB	100 dB	90 dB	90 dB	80 dB
<b>Adapters</b>						
MMCX-to 0.1 in (2.54 mm)	160 dB	100 dB	70 dB	60 dB	40 dB	30 dB
MMCX-to 0.062 in (1.57 mm)	160 dB	100 dB	70 dB	60 dB	40 dB	30 dB

## TIVH 시리즈 공통 모드 제거 비율, 센서 팁 케이블 및 어댑터 (일반)

Sensor tip cable/adaptor	DC	1 MHz	100 MHz	200 MHz	500 MHz	800 MHz
<b>MMCX Sensor tip cables</b>						
IVTIP1X	160 dB	120 dB	120 dB	110 dB	110 dB	110 dB
MMCX10X	160 dB	120 dB	110 dB	102 dB	91 dB	85 dB
MMCX50X	160 dB	116 dB	100 dB	93 dB	85 dB	80 dB
MMCX250X	160 dB	104 dB	85 dB	80 dB	73 dB	70 dB
<b>0.100 in Pitch (2.54 mm) Square Pin sensor tip cables</b>						
SQPIN100X	160 dB	110 dB	60 dB	50 dB	37 dB	30 dB
SQPIN500X	160 dB	100 dB	70 dB	57 dB	39 dB	30 dB
<b>0.200 in Pitch (5.08 mm) Square Pin sensor tip cables</b>						
WSQPIN1000X	160 dB	100 dB	60 dB	47 dB	29 dB	20 dB
WSQPIN2500X	160 dB	100 dB	60 dB	48 dB	33 dB	25 dB
<b>Adapters</b>						
MMCX-to 0.1 in (2.54 mm)	160 dB	85 dB	70 dB	60 dB	40 dB	30 dB
MMCX-to 0.062 in (1.57 mm)	160 dB	85 dB	70 dB	60 dB	40 dB	30 dB

## TIVM 시리즈 최대 비파괴 전압 (일반)

Sensor tip cable	V <sub>pk</sub> (DC + peak AC)	V <sub>RMS</sub>
Sensor head only	4.3 V <sub>pk</sub>	3 V <sub>RMS</sub>
IVTIP1X	4.3 V <sub>pk</sub>	3 V <sub>RMS</sub>
IVTIP5X	21.5 V <sub>pk</sub>	12 V <sub>RMS</sub>
IVTIP10X	43 V <sub>pk</sub>	16 V <sub>RMS</sub>
IVTIP25X	107.5 V <sub>pk</sub>	25 V <sub>RMS</sub>
IVTIP50X	200 V <sub>pk</sub>	35 V <sub>RMS</sub>

**TIVH 시리즈 최대 비파괴 전압 (일반)**

Sensor tip cable	Vpk (DC + peak AC) <sup>3</sup>
Sensor head only	25 Vpk
IVTIP1X	25 Vpk
MMCX10X	250 Vpk
MMCX50X	250 Vpk
MMCX250X	250 Vpk
SQPIN100X	600 Vpk
SQPIN500X	600 Vpk
WSQPIN1000X	2500 Vpk
WSQPIN2500X	2500 Vpk

**Common mode voltage** 60 kV peak

**Common mode input impedance (Typical)**

**Input resistance** Galvanically isolated through the fiber optic connection  
**Input capacitance <sup>4</sup>** < 2 pF

**DC Gain accuracy**

**Differential DC gain accuracy in 1X range**  $\pm 3\% \pm$  DC offset error voltage  $\pm$  input offset accuracy error  
**Differential DC gain accuracy in 2X range** 60% of  $\pm$  Full Scale:  $\pm 3\% \pm$  DC offset error voltage  $\pm$  input offset accuracy error  
 >60% to 80% of  $\pm$  Full Scale: 0% to  $-4\% \pm$  DC offset error voltage  $\pm$  input offset accuracy error  
 >80% to 100% of  $\pm$  Full Scale: 0% to  $-7\% \pm$  DC offset error voltage  $\pm$  input offset accuracy error

**System noise (input referred) (Typical)**

Sensor tip cable/adaptor	1X Range	2X Range
TIVH08/TIVH08L Sensor head input SMA	< 1.2 mV <sub>rms</sub>	< 1.4 mV <sub>rms</sub>
TIVH05/TIVH05L Sensor head input SMA	< 0.72 mV <sub>rms</sub>	< 0.85 mV <sub>rms</sub>
TIVH02/TIVH02L Sensor head input SMA	< 0.61 mV <sub>rms</sub>	< 0.75 mV <sub>rms</sub>
TIVM1/TIVM1L Sensor head input SMA	< 0.8 mV <sub>rms</sub>	< 1.6 mV <sub>rms</sub>
Input referred noise with tip cable	(Sensor head input SMA noise) * (Tip cable attenuation)	(Sensor head input SMA noise) * (Tip cable attenuation)
Examples:	TIVH08 1X Range with MMCX10X tip cable: Noise = (1.2 mV <sub>rms</sub> ) * (10) = 12 mV <sub>rms</sub>	TIVH08 2X Range with MMCX10X tip cable: Noise = (1.4 mV <sub>rms</sub> ) * (10) = 14 mV <sub>rms</sub>

**Propagation delay**

**3 meter fiber cable** 35 ns  $\pm$  5 ns  
**10 meter fiber cable** 68 ns  $\pm$  7 ns

**Laser certification**

CLASS I LASER PRODUCT  
 This product complies with 21 CFR 1040.10 and 1040.11 except for deviations pursuant to Laser Notice No. 50, dated June 24, 2007.

<sup>3</sup> Derated with frequency; refer to the Maximum differential input voltage vs. frequency derating graph in the Specifications section of the TIVH Series IsoVu Measurement System User Manual.

<sup>4</sup> The capacitance between the sensor head and a reference plane. The sensor head is placed six inches (15.25 cm) above the reference plane.

## Ordering information

### TIVM models

TIVM1	Tektronix IsoVu 1 GHz Medium Voltage with 3 m cable
TIVM1L	Tektronix IsoVu 1 GHz Medium Voltage with 10 m cable

### TIVH models

TIVH08	Tektronix IsoVu 800 MHz High Voltage with 3 m cable
TIVH08L	Tektronix IsoVu 800 MHz High Voltage with 10 m cable
TIVH05	Tektronix IsoVu 500 MHz High Voltage with 3 m cable
TIVH05L	Tektronix IsoVu 500 MHz High Voltage with 10 m cable
TIVH02	Tektronix IsoVu 200 MHz High Voltage with 3 m cable
TIVH02L	Tektronix IsoVu 200 MHz High Voltage with 10 m cable

## TIVM series

### Standard accessories

016-2108-xx	IsoVu product carrying case, soft case
016-2110-xx	IsoVu accessories carrying case, soft case
003-1946-xx	Solder aid for 0.062-inch (1.57 mm) pitch square pins (0.016 - 0.018-inch (0.4 - 0.46 mm) square pin installation tool)
IVTIP5X	5X Sensor tip cable
IVTIP25X	25X Sensor tip cable
003-1947-xx	5/16-inch SMA wrench/driver tool
131-9717-xx	Probe tip adapter (blue), MMCX to 0.1-inch (2.54 mm) square pin (0.025-inch (0.635 mm) square pins)
131-9677-xx	Probe tip adapter (white), MMCX to 0.062-inch (1.57 mm) square pin (0.016 - 0.018-inch (0.4 - 0.46 mm) square pins)
020-3169-xx	DUT Interface pin kit with (qty. 20) 0.018-inch (0.46 mm) round solder-in pins
352-1171-xx	Flexible tripod with quick release
344-0693-xx	Flexible tripod feet, 3 each
352-1170-xx	Probe tip tripod support with living hinge, 2 each
071-3495-xx	User manual (English)
---	Certificate of traceable calibration

Translated manuals can be downloaded as pdf files on your local Tektronix Web site.

### Recommended accessories

IVTIP1X	1X Sensor tip cable
IVTIP10X	10X Sensor tip cable
IVTIP50X	50X Sensor tip cable

## TIVH series

### Standard accessories

016-2108-xx	IsoVu product carrying case, soft case
016-2110-xx	IsoVu accessories carrying case, soft case
MMCX50X	50X Sensor tip cable
SQPIN500X	500X Sensor tip cable
003-1947-xx	5/16-inch SMA wrench/driver tool
131-9717-xx	Probe tip adapter (blue), MMCX to 0.1-inch (2.54 mm) square pin (0.025-inch (0.635 mm) square pins)
352-1171-xx	Flexible tripod with quick release
344-0693-xx	Flexible tripod feet, 3 each
352-1170-xx	Probe tip tripod support with living hinge, 2 each
071-3556-xx	User manual (English)
—	Certificate of traceable calibration

Translated manuals can be downloaded as pdf files on your local Tektronix Web site.

### Recommended accessories

003-1946-xx	Solder aid for 0.062-inch (1.57 mm) pitch square pins (0.016 - 0.018-inch (0.4 - 0.46 mm) square pin installation tool)
131-9677-xx	Probe tip adapter (white), MMCX to 0.062-inch (1.57 mm) square pin (0.016 - 0.018-inch (0.4 - 0.46 mm) square pins)
020-3169-xx	DUT Interface pin kit with (qty. 20) 0.018-inch (0.46 mm) round solder-in pins
IVTIP1X	1X Sensor tip cable
MMCX10X	10X Sensor tip cable
MMCX250X	250X Sensor tip cable
SQPIN100X	100X Sensor tip cable
WSQPIN1000X	1000X Sensor tip cable
WSQPIN2500X	2500X Sensor tip cable

## Supported oscilloscopes

The measurement systems can be used with the following Tektronix oscilloscopes. For oscilloscopes not included in this list, contact your local Tektronix representative.

- 5 Series MSO (WSQPIN2500X tip cables require V1.6 or later oscilloscope firmware)
- MDO3000 series (WSQPIN tip cables require V1.26 or later oscilloscope firmware)
- MDO4000C series (WSQPIN tip cables require V1.06 or later oscilloscope firmware)
- MSO/DPO/MDO4000B series (WSQPIN tip cables are not compatible)
- MSO/DPO5000B series
- DPO7000C series

In addition to the above oscilloscopes, the TIVH and TIVM measurement systems can also be used with the following oscilloscopes with a TCA-VPI50 adapter.

- MSO/DPO70000C series
- MSO/DPO70000DX series
- DPO70000SX series

## Options

### Service options

<b>Opt. C3</b>	Calibration Service 3 Years
<b>Opt. C5</b>	Calibration Service 5 Years
<b>Opt. D1</b>	Calibration Data Report
<b>Opt. D3</b>	Calibration Data Report 3 Years (with Opt. C3)
<b>Opt. D5</b>	Calibration Data Report 5 Years (with Opt. C5)
<b>Opt. G3</b>	Complete Care 3 Years (includes loaner, scheduled calibration, and more)
<b>Opt. R3</b>	Repair Service 3 Years (including warranty)
<b>Opt. R5</b>	Repair Service 5 Years (including warranty)

Probes and accessories are not covered by the oscilloscope warranty and Service Offerings. Refer to the datasheet of each probe and accessory model for its unique warranty and calibration terms.

**ASEAN / Australasia** (65) 6356 3900  
**Belgium** 00800 2255 4835\*  
**Central East Europe and the Baltics** +41 52 675 3777  
**Finland** +41 52 675 3777  
**Hong Kong** 400 820 5835  
**Japan** 81 (3) 6714 3086  
**Middle East, Asia, and North Africa** +41 52 675 3777  
**People's Republic of China** 400 820 5835  
**Republic of Korea** +822 6917 5084, 822 6917 5080  
**Spain** 00800 2255 4835\*  
**Taiwan** 886 (2) 2656 6688

**Austria** 00800 2255 4835\*  
**Brazil** +55 (11) 3759 7627  
**Central Europe & Greece** +41 52 675 3777  
**France** 00800 2255 4835\*  
**India** 000 800 650 1835  
**Luxembourg** +41 52 675 3777  
**The Netherlands** 00800 2255 4835\*  
**Poland** +41 52 675 3777  
**Russia & CIS** +7 (495) 6647564  
**Sweden** 00800 2255 4835\*  
**United Kingdom & Ireland** 00800 2255 4835\*

**Balkans, Israel, South Africa and other ISE Countries** +41 52 675 3777  
**Canada** 1 800 833 9200  
**Denmark** +45 80 88 1401  
**Germany** 00800 2255 4835\*  
**Italy** 00800 2255 4835\*  
**Mexico, Central/South America & Caribbean** 52 (55) 56 04 50 90  
**Norway** 800 16098  
**Portugal** 80 08 12370  
**South Africa** +41 52 675 3777  
**Switzerland** 00800 2255 4835\*  
**USA** 1 800 833 9200

\* European toll-free number. If not accessible, call: +41 52 675 3777

**For Further Information.** Tektronix maintains a comprehensive, constantly expanding collection of application notes, technical briefs and other resources to help engineers working on the cutting edge of technology. Please visit [www.tek.com](http://www.tek.com).

Copyright © Tektronix, Inc. All rights reserved. Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX and TEK are registered trademarks of Tektronix, Inc. All other trade names referenced are the service marks, trademarks, or registered trademarks of their respective companies.



07 Feb 2018 51W-61217-2

[www.nubicom.co.kr](http://www.nubicom.co.kr)



<p>서울본사</p> <p>대전지사</p>	<p>서울특별시 영등포구 경인로 775(문래동 3가, 에이스하이테크시티 3동 2층 201호) TEL: 070-7872-0701 FAX: 02-2167-3801 E-mail: sales@nubicom.co.kr</p> <p>대전광역시 유성구 덕명동로 22번길 10 TEL: 070-7872-0712 FAX: 02-2167-3801 E-mail: jbkim@nubicom.co.kr</p>
-------------------------	---